Product data sheet

EST-PA2650B

Power amplifier D-Class 2x650 Watt

Overview

The Amplifiers are designed for perfect integration into the EDWARDS solutions. Thanks to their flexibility, they can also be used for any other Public Address and Voice Evacuation applications. These amplifiers have been developed to meet the specific requirements of the EN 54-16 standard for safety installations.

The EST-PAXXXXB is a family of 2U, rackmountable, 8-channel (EST-PA8080B, EST-PA8160B), 4-channel (EST-PA4160B),2 channel (high power EST-PA2650B) and 1 channel (EST-PA1650B) class-D transformer isolated power amplifiers for 50 V and 100 V distributed loudspeaker systems. Amplifier EST-PA8080B can deliver up to 8 x 80 W, for EST-PA8160B and EST-PA2650B delivering power increases respectively to the 8 x 160 W and 2 x 650 W. In a bridged mode amplifier channels are combined and can deliver 4 x 160 W for EST-PA8080B, 4 x 320 W for EST-PA8160B and 1 x 1300 W for EST-PA2650B. These amplifiers have 48 VDC input which allows to connect with battery backup system for maximum availability and durability in an voice evacuation system.

The EST-PAXXXXB amplifiers are powered from external power supply module EST-PS48800 working in a block. The current from block is distributed to individual amplifiers through the “power manager” EST-PSM48 (device includes a battery charger and is in compliance with EN 54-4).



Details

- Front panel indicators include: Supply / Active / Fault
- 100 / 50 Volt available via terminal blocks at the rear
- Output channels can be linked into: 1 x 1300 W by daisy-chaining 50 V tapping (input on parallel)
- EST-PAXXXXB combines with the EST-PSM48 Power Supply Manager (charger and back-up supply)

EST-PA2650B

Power amplifier D-Class 2x650 Watt

Technical specifications

Eléctrico

Tipo de fuente de alimentación	48 VCC
Consumo de corriente	0.15 A (at 48 VDC, Standby) 0.33 A (at 48 VDC, Active) 38 A (at 48 VDC, Max. nominal current)
Voltaje de funcionamiento	42-57 V

Físico

Peso neto	15 kg
Peso de envío	16.2 kg

Estándares y regulaciones

Normativas	EN54-16

Electrical

DC fuse rating (internal)	2 x 15 AF- H 2 x 7.5 AF- H
Overall power efficiency nominal DC input max output power at 1 kHz	80%

Amplifier

Continuous nominal output power per channel, all channels driven into nominal load at 1 kHz 30°C ambient	650 W 15.4 Ω / 200 nF
Continuous nominal output power per channel, all channels driven into nominal load at 1 kHz 55°C ambient	TBA
Nominal balanced input level for 100 V output at 1 kHz and nominal load	1 V
Balanced input level trim range for 100 V output at 1 kHz and nominal load *	0,95 – 3 V
Max balanced input level	3 V
Input impedance at 1 kHz	22 kΩ
Input common mode rejection at <1 kHz	> 61 dB
Frequency response (-6 dB)	75 Hz – 22 kHz 15.4 Ω / 200 nF
S/N ref nominal power at 1 kHz 22 Hz – 22 kHz	> 85 dB 15.4 Ω / 200 nF
THD power 1 kHz (42 V – 57 V)	< 10%
Crosstalk between channel 50 Hz – 20 kHz nominal load dB	< -70 dB 15.4 Ω / 200 nF

Physical

Front panel width	482 mm
Back panel width	445 mm
Height	88.5 mm
Packaging dimensions	150 x 530 x 610 mm (W x H x D)
DC input socket	DG58C-A-2P13
Audio output socket	3 pin PHOENIX 5.08 mm
Nominal output voltage taps	50 / 100 V

Como empresa innovadora, Carrier Fire & Security se reserva el derecho de modificar las especificaciones de los productos sin previo aviso. Para conocer las últimas especificaciones de los productos, visite la Web de es.firesecurityproducts.com o póngase en contacto con su comercial.

Last updated on 14 September 2021 - 11:12