

Mini50

Bluetooth Wall-mounted Amplifier



Features

- Built-in 2x60W stereo Class D amplifier
- 8Ω speaker output
- Support wireless Bluetooth 5.0 and USB input
- 5 pre-set EQ mode available
- 1 AUX input and 1 AUX output for power extension
- With remote controller for convenient use
- Aluminum-alloy casing, small size and portable
- Power supply:DC12-24V/3-5A

Descriptions

Mini50 is a portable mixer amplifier with USB and Bluetooth, it has 1 Aux input and 1 Aux output for power extension, support 8Ω speaker output,whats more, it have small size but big power, it's 2 channels stereo speaker output, rated power is 2x60W. The device can meet the requirements of the users and can be widely applied in classroom, stores, Coffee shop and other small place.

Specifications

Item	Mini50
Rated Power	2×60W
Impedance	8Ω
Freq. Resp.	20Hz-32KHz
Distortion	≤0.06%(1KHz/10W)
SNR	> 92dB
LINE IN Sensitivity	0dB(1V)
LINE IN Impedance	47KΩ
LINE Out Sensitivity	2V(Max)
LINE Out Impedance	47KΩ
BT Transmission	10m
BT Standard	BT5.0
Audio format	APT, FLAC, WAV, MP3, APE etc
Power Supply	DC12-24V/3-5A
Net Weight	0.33KG
Gross Weight	0.35KG
Product Dimension	138mm×55mm×136mm