

54V DC, 2.78A 150W Power Adapter

48VDC3000 (V3)

- 54V DC, 2.78A 150W power adapter
- Reliable performance
- Includes 1.8m / 5.9 ft. power cord
- Compatible with select TRENDnet industrial switches
- NDAA / TAA compliant (U.S. and Canada only)

Optional Power Adapter for select TRENDnet industrial switches.

Compatible Models			
TI-G50611	TI-G5091	TI-G5062	TI-G51SC
TI-G102	TI-F711SFP v1	TI-BF711SFP v1	TI-P11SFP v3
TI-BG104	TI-BG50611	TI-BG5091	TI-PG160
TI-PG162	TI-PG50F v1/v2	TI-PG80F v1/v2	TI-PG62F v1
TI-PG102F v1	TI-PG541i v1/v2	TI-PG541 v1/v2/v3	TI-PG743Bi
TI-PG102 v1	TI-UF11SFP v3		

SPECIFICATIONS

Interface
- 4-Pin DIN power connector
- Input: 100 - 240V AC, 50/60 Hz, 2.8 A
- Output: 54V DC, 2.78A, 150W (max.)

Operating Temperature
- - 30° – 70° C (- 22° – 158° F)

Operating Humidity
- Max. 95% non-condensing

Dimensions
- 155 x 70 x 30mm (6.1 x 2.8 x 1.4 in.)

Weight
- 471g (16.6 oz.)

Warranty
- 1-year limited

Package Contents
- 48VDC3000
- Power cord (1.8m / 5.9 ft.)

All references to speed are for comparison purposes only. Product specifications, size, and shape are subject to change without notice, and actual product appearance may differ from that depicted herein.

20675 Manhattan Place • Torrance • CA 90501 • USA • T: 1-888-326-6061 • sales@trendnet.com • www.TRENDnet.com

TRENDnet is a registered trademark. Other Brands and product names are trademarks of their respective holders. Information provided in this document pertain to TRENDnet products and is subject to change at any time, without notice. For the most recent product information please visit http://www.trendnet.com. Copyright © TRENDnet. All Rights Reserved.

Updated: 2/11/2026